

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Deterministic initial ranging burst size	
Date Submitted	2005-03-15	
Source(s)	Joël Demarty SEQUANS Communications. joel@sequans.com Voice: +33 1 44 89 48 07 Ambroise Popper SEQUANS Communications ambroise@sequans.com David A Castelow, Eyal Verbin Airspan Communications, Cambridge House, Oxford Road, Uxbridge, UK mailto:dcastelow@airspan.com Voice: +44 1895 467281 Giulio Cavalli Siemens Comm. giulio.cavalli@siemens.com	
Re:	IEEE P802.16REVd/D5-2004	
Abstract	Clarification on ambiguities on the size of the initial ranging burst in OFDM.	
Purpose	Adopt changes.	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chair@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.	

Deterministic Initial Ranging Burst Size in OFDM

Joël Demarty, Ambroise Popper (SEQUANS Communications)

David A. Castelow, Eyal Verbin (Airspan Communications)

Giullio Cavalli (Siemens Communications)

1. Introduction

IEEE 802.16-2004 has some imprecision relative to the size of the initial ranging request and whether the SS is supposed to send just the number of symbols necessary for a RNG-REQ message or supposed to transmit using stuffing during the entire size of an opportunity?

1.1. Size of the initial RNG-REQ message

The initial RNG-REQ has a variable length. In OFDM, the smallest RNG-REQ packet is 23 bytes, taking into account the mandatory CRC. It fits in 4 OFDM symbols.

However, there is an optional TLV (AAS broadcast capability) that may add 3 bytes to the RNG-REQ message. This makes the RNG-REQ message 27-bytes long or 5 OFDM symbols.

Moreover, nothing in the specification prevents an SS to add other TLVs in the RNG-REQ. It happens with SC/SCa PHY but it is also possible in future extensions of the standard, like all the RNG-REQ TLVs related to mobility introduced in 802.16e. These extra TLVs could also be special vendor-specific TLVs or even Ranging Anomalies although the spec writes that it "may be included in the RNG-REQ message after the SS has received an RNG-RSP addressed to the SS:"

Because of this imprecision, the BS can not determine easily the size of the RNG-REQ message and consequently the size of the initial ranging burst. If not fixed, this would cause interoperability issues if the BS expects a burst too small compared to the actual burst sent by the SS. The SS would not enter the network.

1.2. Size of the initial RNG-REQ burst

There is also an ambiguity on the size of the initial ranging burst.

In IEEE802.16-2004, there is a statement (page 450, line 28) that requires the SS to transmit during an UL allocation. *"An SS shall transmit during the entirety of all of its UL allocations, using the standard padding mechanism (6.3.3.7) to fill allocations if necessary."*

Without any restriction, it also applies to initial ranging contention opportunities and bandwidth request contention opportunities. This sentence is valid for BW contention TOs, but not for IR contention TOs.

We should add a restriction in the spec that it does not apply to IR contention TOs.

This is especially important because there is another problematic sentence in the description of the "Ranging Request Opportunity Size" UCD TLV: "Size (in units of PS) of PHY bursts that an SS may

use to transmit a RNG-REQ message in a contention ranging request opportunity. The value includes all PHY overhead as well as the maximum SS/BS round trip propagation delay."

This sentence, along with the previous one, seems to require the SS to transmit its PHY burst during the whole IR TO.

This ambiguity is serious because the SS is not yet synchronized with BS. Should the SS apply this requirement blindly, its initial ranging burst would collide with burst sent in the allocations following the initial ranging opportunities.

1.3. Proposed Solution

The simplest solution is to have a TLV in the UCD to specify the burst size expected by the BS. This is very important because the size of the IR TO (as described in the UCD) takes into account the max supported round trip delay and gives no indication of the maximum burst size supported inside this TO.

The easiest fix is to add "ranging request burst size" TLV .

This contribution amends changes made in IEEE P802.16-2004/Cor1/D1.

2. Text changes

[Insert the following text page 38, line 40]

6.3.9.5.1 Contention based Initial ranging and automatic adjustments

Change second paragraph as indicated:

For SC, SCa, and OFDM PHY, the SS shall put together a RNG-REQ message to be sent in an Initial Ranging Interval. The duration of the burst carrying the RNG-REQ message shall be as specified in the "Ranging Request Burst Size" TLV (See 11.3.1). The CID field shall be set to the non initialized SS value (zero). For the OFDMA PHY, the initial ranging process shall begin by sending initial-ranging CDMA codes on the UL allocation dedicated for that purpose (for more details see 6.3.10.3), instead of RNG-REQ messages sent on contention slots.

[Insert the following text page 127 , line 50]

Delete the entry with 'Ranging request opportunity size' under the Name column from Table 349.

Insert the following entry to tables 350, 351

<u>Contention ranging request opportunity size</u>	<u>XX</u>	<u>2</u>	<u>Size (in units of PS) of the transmission opportunity that an SS may use to transmit a RNG-REQ message in a contention ranging request opportunity. The value includes all PHY overhead as well as the maximum SS/BS round trip propagation delay</u>
--	-----------	----------	--

<u>Contention ranging request burst size</u>	<u>XX</u>	<u>2</u>	<u>Size (in units of PS) of PHY bursts that an SS shall use to transmit a RNG-REQ message in a contention ranging request opportunity.</u>
--	-----------	----------	--

Insert the following entry to tables 352

Contention ranging request opportunity size	<u>XX</u>	<u>2</u>	<u>Size (in unit of PS) of the transmission opportunity that an SS may use to transmit a RNG-REQ message in a contention ranging request opportunity. The value includes all PHY overhead as well as the maximum SS/BS round trip propagation delay</u>
<u>Contention ranging request burst size</u>	<u>XX</u>	<u>2</u>	<u>Size (in OFDM symbols) of PHY bursts that an SS shall use to transmit a RNG-REQ message in a contention ranging request opportunity.</u> <u>Default value: 4</u>