

Project	<b>IEEE 802.16 Broadband Wireless Access Working Group</b> < <a href="http://ieee802.org/16">http://ieee802.org/16</a> >	
Title	<b>RS support for OFDMA Based Ranging</b>	
Date Submitted	<b>2006-11-07</b>	
Source(s)	Shashikant Maheshwari, Yousuf Saifullah, Haihong Zheng Nokia 6000 Connection Drive, Irving, TX	Voice: 972 839 1878 Fax: <a href="mailto:shashikant.maheshwari@nokia.com">shashikant.maheshwari@nokia.com</a> , <a href="mailto:Yousuf.saifullah@nokia.com">Yousuf.saifullah@nokia.com</a> , <a href="mailto:haihong.1.zheng@nokia.com">haihong.1.zheng@nokia.com</a>
Re:	This is in response to the call for proposal, 80216j-06_027.pdf, sent out by 802.16j TG.	
Abstract	This contribution proposes RS support for MS Initial and Periodic Ranging in multi-hop system.	
Purpose	Add proposed spec changes.	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < <a href="http://ieee802.org/16/ipr/patents/policy.html">http://ieee802.org/16/ipr/patents/policy.html</a> >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < <a href="mailto:chair@wirelessman.org">mailto:chair@wirelessman.org</a> > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < <a href="http://ieee802.org/16/ipr/patents/notices">http://ieee802.org/16/ipr/patents/notices</a> >.	

## RS support for OFDMA Based Ranging

*Shashikant Maheshwari, Yousuf Saifullah and Haihong Zheng*

*Nokia*

### Introduction

As defined in IEEE 802.16-2004 & IEEE 802.16e-2005, network entry procedure for OFDMA PHY can be described in two steps.

- CDMA contention based initial ranging and automatic adjustments
- CID allocation and remaining network entry procedure

The CDMA contention based initial Ranging procedure (step 1) may take multiple iterations over the air interface. In 802.16j system, there could be one or more RS between MMR-BS and MS. The CDMA based initial ranging has to traverse over the multiple hops of the air interface. This would cause increased delay and it is spectrally inefficient. This contribution proposes that CDMA contention based initial ranging and automatic adjustments should be performed by access RS (last hop RS) while the CID allocation and remaining network entry procedure are desired to be performed by the BS. In addition this contribution also proposes that CDMA contention based periodic ranging and automatic adjustments should also be performed by access RS without involving MMR-BS.

This contribution assumes that MMR-BS manages and maintains the MS context. In addition, RS may maintain some of MS context. MMR-BS shall be responsible for the allocation of CIDs and other parameters. It is assumed that RS transmits its own preamble. This contribution does not exclude any type of scheduling, both centralized and distributed scheduling is assumed.

### CDMA contention based initial ranging and automatic adjustments in 802.16j system

In 802.16j system, there could exist one or more RS between MMR-BS and MS. MS after synchronization with RS and receiving downlink and uplink parameters, shall perform the CDMA contention based initial ranging with access RS. Access RS will process the MS's CDMA ranging request and locally adjust the access link and manages the MS's timing, power and frequency offsets. Access RS as part of CDMA contention based initial ranging process will require to send RNG\_RSP and at some point CDMA\_Alloc\_IE() to MS on the access link. Procedure to send these messages to MS will depend on RS capability and scheduling scheme implemented at access RS. This is described in detail in section [Bandwidth request and scheduling]

Access RS shall relay all the other messages (including complete RNG\_REQ/RNG\_RSP) between MMR-BS and RS. MS context shall be anchored at MMR-BS. It is desired that MMR-BS shall allocate parameters (Basic, primary CID etc.) and process remaining network entry procedure for MS. RS can perform the bandwidth request to upstream node (BS/RS) either in parallel or sequential to get the UL allocation and use that allocation to transmit MS's completes RNG\_REQ.

### CDMA contention based periodic ranging and automatic adjustments in 802.16j system

In 802.16j system, there could exist one or more RS between MMR-BS and MS. MS that chooses to initiate periodic ranging shall perform the CDMA contention based periodic ranging with access RS (last hop RS,

attached directly with MS). Access RS will process the MS's CDMA ranging request and locally adjust the RS-MS link and manages the MS's timing, power and frequency offsets.


### **Bandwidth request and scheduling**

This contribution propose that access RS will manage access link locally. However, scheduling of RNG\_RSP and CDMA\_Alloc\_IE() messages on the RS-MS link depends upon the access RS capability (centralized or distributed).

For the message transmission on the relay link, access RS should utilize already specified methods for Bandwidth request in IEEE 802.16-2004 & IEEE 802.16e-2005 Std to request resources for sending complete RNG\_REQ to BS or may utilize methods defined in contribution C802.16-06\_189.pdf.


### Centralized scheduling

In case of centralized scheduling, all the allocation of radio resources and transmission of messages are centrally controlled by the MMR-BS. In order to send RNG\_RSP and CDMA\_ALLOC\_IE() on the access link, access RS will require to send bandwidth request to MMR-BS. Figure 1 below shows the message sequence diagram for proposed procedure in case of centralized scheduling.



### Distributed scheduling

In case of distributed scheduling with central co-ordination with BS, access RS shall schedule RNG\_RSP and CDMA\_Alloc\_IE() on its own. Figure 2 below shows the message sequence diagram for the proposed procedure in case of distributed scheduling.



## Advantages

- Reduces overall latency for MS's initial ranging process. The main time consuming step of back and forth ranging with CDMA code is done only on the access link.
- Proposed scheme does not require RS to relay CDMA Ranging codes and adjustment parameters back to BS, therefore it is spectrally efficient. It saves bandwidth on both DL and UL.

## Changes to the specification

### 6.3.10.3 OFDMA-based ranging

*Insert the following at the end of the subclause:*

When one or more RS introduced between the MMR-BS and MS. MS shall perform the CDMA contention based ranging process with access RS (last hop RS, attached directly with MS) as defined in section 6.3.10.3.1 and 6.3.10.3.2. Access RS will process the MS's CDMA ranging request and locally adjust the RS-MS link (access link) and manages the MS's timing, power and frequency offsets. Access RS as part of CDMA contention based initial ranging process also require to send RNG\_RSP and at some point CDMA\_Alloc\_IE() to MS on the RS-MS link. Procedure to send these messages to MS will depend on RS capability and scheduling scheme implemented at access RS. In case of centralized scheduling, access RS shall request the transmission opportunity for RNG\_RSP and CDMA\_alloc\_IE() from upstream node (RS or MMR-BS) and in case of distributed scheduling, access RS shall schedule transmission of RNG\_RSP and CDMA\_ALLoc\_IE() on its own.


#### 6.3.10.3.1 Contention-based initial ranging and automatic adjustments

*Change the text as indicated:*

- The SS, after acquiring downlink synchronization and uplink transmission parameters, shall choose randomly a Ranging Slot (with the use of a binary truncated exponent algorithm to avoid possible re-collisions) at the time to perform the ranging, then it chooses randomly a Ranging Code (from the Initial Ranging domain) and sends it to the BS/RS (as a CDMA code).
- The BS/RS cannot tell which SS sent the CDMA ranging request; therefore, upon successfully receiving a CDMA Ranging Code, the BS/RS broadcasts a Ranging Response message that advertises the received Ranging Code as well as the ranging slot (OFDMA symbol number, subchannel, etc.) where the CDMA Ranging code has been identified. This information is used by the SS that sent the CDMA ranging code to identify the Ranging Response message that corresponds to its ranging request. The Ranging Response message contains all the needed adjustment (e.g., time, power, and possibly frequency corrections) and a status notification. Depending upon the RS capability, RS may need to request resources from BS for transmission of Ranging Response message on the access link.
- Upon receiving a Ranging Response message with continue status, the SS shall continue the ranging process as done on the first entry with ranging codes randomly chosen from the Initial Ranging domain sent on the Periodic Ranging region.
- When the BS/RS receives an initial-ranging CDMA code that results in sending an RNG-RSP message with success status, the BS/RS shall provide BW allocation for the SS using the CDMA\_Allocation\_IE to send an RNG-REQ message. Depending upon the RS capability, RS may need to request resources from BS for transmission of Ranging Response message and CDMA\_Allocation\_IE on the access link.
- Initial ranging process is over after receiving RNG-RSP message, which includes a valid basic CID (following a RNG-REQ transmission on a CDMA\_Allocation\_IE). If this RNG-RSP message includes 'continue' indication, the ranging process should be continued using the periodic ranging mechanisms.

- The timeout required for SS to wait for RNG-RSP, following or not following CDMA Allocation IE, is defined by T3.
- Using the OFDMA ranging mechanism, the periodic ranging timer is controlled by the SS, not the BS.

**Change Table 121 as indicated:**



parameters

[Time to send the next map]  
Send map containing  
anonymous BW allocation  
with original Ranging Code  
and Ranging Slot

-----UL-MAP----->


RS May need to request transmission  
opportunity from upstream node (RS/BS)

<-----RNG-REQ-----

Transmit RNG-REQ and  
continue with regular Initial  
network entry

***replace title of figure 87 from “Figure 87—CDMA Initial Ranging—SS” to “Figure 87—CDMA Initial Ranging—BS/RS (Distributed scheduling)”***

***Insert following new figures 87a***



**Figure 87a – CDMA Initial Ranging – RS (centralized scheduling)****6.3.10.3.1 Periodic ranging and automatic adjustments**

*Change the text as indicated:*

An SS that wishes to perform periodic ranging shall take the following steps:

- The SS, shall choose randomly a Ranging Slot (with the use of a binary truncated exponent algorithm to avoid possible re-collisions) at the time to perform the ranging, then it chooses randomly a Periodic Ranging Code (from the Periodic Ranging domain) and sends it to the BS/RS (as a CDMA code).
- If the MS does not receive a response, the MS may send a new CDMA code at the next appropriate periodic Ranging transmission opportunity and adjust its power level up to PTX\_IR\_MAX (6.3.9.5.1).
- The BS/RS cannot tell which SS sent the CDMA ranging request; therefore, upon successfully receiving a CDMA Periodic Ranging Code, the BS/RS broadcasts a Ranging Response message that advertises the received Periodic Ranging Code as well as the ranging slot (OFDMA symbol number, subchannel, etc.) where the CDMA Periodic Ranging code has been identified. This information is used by the SS that sent the CDMA Periodic ranging code to identify the Ranging Response message that corresponds to its ranging request. The Ranging Response message contains all the needed adjustment (e.g., time, power, and possibly frequency corrections) and a status notification. Depending upon the RS capability, RS may need to request resources from BS for transmission of Ranging Response message on the access link.
- Upon receiving a Ranging Response message with continue status, the SS shall continue the ranging process with further periodic ranging codes randomly chosen from the Periodic Ranging domain.
- Using the OFDMA ranging mechanism, the periodic ranging timer is controlled by the SS, not the BS/RS.
- The BS/RS may send an unsolicited RNG-RSP as a response to a CDMA-based bandwidth-request or any other data transmission from the SS.

**Replace title of figure 88 from “Figure 88—Periodic CDMA Ranging—BS” to “Figure 88—Periodic CDMA Ranging—BS/RS (Distributed scheduling)”**

**Replace title of figure 89 from “Figure 89—Periodic Ranging—Received ranging code -BS” to “Figure 89—Periodic Ranging—Received ranging code -BS/RS (Distributed scheduling)”**

**Insert following new figures 89a**




Figure 89a – CDMA Periodic Ranging – RS (centralized scheduling)